

## Sound Craft FX16 mixer

<b>Type</b>	Analog
<b>Channels</b>	16
<b>Inputs - Mic Preamps</b>	16 x XLR
<b>Phantom Power</b>	16
<b>Inputs – Line</b>	16 x 1/4" (CH 1-16), 2 x RCA (2 TRK)
<b>Outputs – Main</b>	2 x XLR (main out), 1 x 1/4" (mono), 2 x 1/4"
<b>Outputs – Direct</b>	16 x 1/4"
<b>Outputs – Other</b>	2 x 1/4" (Sub)
<b>Headphones</b>	1 x 1/4"
<b>EQ Bands</b>	3-band, Sweepable Mid
<b>Effects</b>	Yes
<b>Channel Inserts</b>	2 x 1/4" (Mix Inserts), 2 x 1/4" (Sub Inserts)
<b>Aux Sends</b>	2 x Pre, 1 x Pre/Post, 1 x FX
<b>Send/Return</b>	I/O 3 x 1/4" (Aux), 6 x 1/4" (Return)
<b>Busses/Groups</b>	2 x Bus (Sub)
<b>Faders</b>	20 x 100mm
<b>Rackmountable</b>	Yes
<b>Height</b>	5.83"
<b>Width</b>	17.46"
<b>Depth</b>	17.42"
<b>Weight</b>	19 lbs.

