

## Yamaha MG24 Mixer

<b>Mixing channels</b>	24 Mono + 4 Stereo
<b>GROUP</b>	4
<b>Input channel functions</b>	CH1-16 HPF, 3-band
<b>midsweep PEQ, Intert I/O;</b>	
<b>CH17-24</b>	4-band PEQ
<b>Output channel functions</b>	LPF on Mono out
<b>On-board processors</b>	2x SPX
<b>Mic inputs</b>	16
<b>Phantom power</b>	+48V DC; ON/OFF per 8ch
<b>Line inputs</b>	4x Stereo
<b>Control and others</b>	Foot switch
<b>Total harmonic distortion</b>	Less than 0.1%
<b>Frequency response</b>	0, +1.0, -3dB 20Hz-20kHz
<b>Equivalent input noise</b>	-128dBu
<b>Residual output noise</b>	-99dBu
<b>Crosstalk</b>	-70dB
<b>Power requirements</b>	Depend on area of purchase; AC100V, 120V or 220-240V; 50/60Hz
<b>Power consumption</b>	100W
<b>Dimensions w x h x d</b>	819mm x 140mm x 551mm
<b>Net weight</b>	18.5kg; 40.8lbs
<b>Accessories Owner's Manual, AC Power cord</b>	

